




## SD CARD RE-ETCHING INSTRUCTIONS

Preparatory Steps to Save Information on the SD Card:	1
Removing Micro SD Card from Titan:	1
Etching Micro SD Card:	2

### Preparatory Steps to Save Information on the SD Card:

1. Enter the Backup & Restore menu  by pressing the icon in the top right section of the header.
2. In the text box labeled “Enter custom name for a backup” enter some name for your backup file. Press the  button to create the backup file.
3. The new file should appear in the list. Select the  icon next to the new backup file.
4. A file explorer will open allowing you to choose your USB drive on the left side. Select the drive and choose “Open”.
5. Once completed pull the USB from the unit and place it into a PC.
6. There should be a new zip file with a title representing the date and time along with the backup filename.

### Removing Micro SD Card from Vulcan:

1. Power your unit down and pull the power cable from the back of your unit.
2. Open the top of your machine.
3. Pull the micro SD card out of the unit. This should take minimal force. It may be useful to use pliers to reach the micro SD card.

## Etching Micro SD Card:

1. Download the [CureControl .img for Pro Electronics Kit](https://www.langmuirsystems.com/downloads) file from:  
<https://www.langmuirsystems.com/downloads>
2. Download BalenaEtcher from <https://etcher.balena.io/>.
  - a. Select “Download Etcher”. Select the correct version for your PC and click the “Download” button.
  - b. Once downloaded, run the installation.
3. Insert a micro SD card into the PC.
4. Once installed, open BalenaEtcher.
5. Select the image file and micro SD card that you wish to etch.
6. Select the “Flash!” button.
7. Once completed remove the micro SD card from the PC.
8. The SD card is now ready to be installed in your machine.